

TERASCAN™ HAND HELD METAL DETECTOR ESH-10

FEATURES

- Detects items of all types of metal : ferrous and non ferrous
- Choice of sound alarm or silent vibrate alarm
- Easy to use, 3 position switch for power, sound and vibrate
- Sensitivity setting at optimum level-no tuning required
- uses one 9 Volt battery
- Low Battery Indicator
- Manufactured in Gray. Flame resistance
- Quick-change Battery compartment
- Charger Jack



INDICATORS

| | |
|-------------------------|-----------------------|
| Solid Yellow LED : AL | Target Detected |
| Flashing Green LED : PW | Power ON |
| Flashing Red LED : BT | Low Battery Indicator |

ALARM SIGNAL

Sound Mode : Buzzer with Red LED
Vibrate Mode : Vibrator with Red LED

CONTROL

3 Way Switch
Forward Position : S Sound ON
Center Position : O Power OFF
Back Position : V Vibrate ON

BATTERY

Single 9 Volt ALKALINE or Ni-Cd
Battery Life : 30 to 40 hours (Ni-Cd)
28 hours (ALKALINE)

DIMENSION

Weight : 6.88ounces (195g)
Length : 14.76" (375mm)
Width : 3.03" (77mm)
Thickness : 1.02" (26mm)

OPERATING TEMP

-15°C to +45°C